



Sample image

KG10A

Type Size: S0

Classification Contact: Rigid contact bridge

Classification Contact Mat: Silver

Classification Terminal: Screw terminal

			E 0660 Teil 107					
Rated insula	ition voltag	e Ui						
				Voltage	, ,			
	4.4				690 AC			
		nd voltage Uimp						
Voltag	ie (KV) – O	vervoltage categ	gory Pollution	degree Supply s	ystem			Function
	4 II		3	Valid for	lines with grounded com	non neutral termination		Switch / Switch disconnector
Rated uninte	errupted cu	rrent lu/Ith						
Current (A)	Ambient	temperature (°C)	Peak temperature (°C)	additional requirements			
	20		50	55	Ambient temperature +5	60°C during 24 hours with pea	ks up to +55°C	
		thermal current	t Ithe					
Current (A)	Ambien	t temperature (°C)	Peak temperature (°C)	Additional requirements		No. of stages (from - to)	Mounting	Mounting size
20		35	40	Ambient temperature +35° peaks up to +40°C	°C during 24 hours with	-		-
Rated opera	tional curre	ent le						
Jtilization ca	ategory					Voltage (V)		Current
AC-15						220 - 240		
AC-15						380 - 440		
AC-20A						690		
AC-21A						20 - 690		
AC-22A						220 - 500		
AC-22A						660 - 690		
Rated opera		er						
Jtilization ca	ategory			Voltage (V)	No. of phases	No.	of poles	Power (k
AC-3				220 - 240	3		3	2
AC-3				380 - 440	3		3	3
/C-3 /C-3				500 - 500 660 - 690	3		3	3,
AC-3				220 - 240	3 1		2	1
AC-3				380 - 440	1		2	1,
AC-23A				220 - 240	3		3	I,
AC-23A				380 - 440	3		3	5
AC-23A				500 - 500	3		3	5
AC-23A				660 - 690	3		3	5
AC-23A				220 - 240	1		2	1
AC-23A				380 - 440	1		2	2
Max Fuse Ra	ating IEC							
use charact	teristic					No. of Fuses		Current
јG						1		
JL60947	-4-1 , UI	-508						
Rated insula	ition voltag	e Ui						
				Voltage				
	.1				300 AC			
Rated therm	al current		Ourrant (4)		Ambiantt	oroturo (°C) Additional Tari		
			Current (A) 20		Ambient temp	erature (°C) Additional Text 0 - 40		



General Information

Text

- The operating handle and position indicating means to be used with these manual motor controllers should be provided from the manufacturer, or the operating handle and position indicating means to be used should have been previously evaluated in combination with the manual motor controllers.
- When intended for use as a motor disconnector the device shall be provided with a method of being locked in the OFF-position.

ated insulation voltage Ui						
ated insulation voltage of		Voltage (V)	AC/DC			
		300	AC			
ated thermal current						
	Current (A)		Ambient temperature			
	20		0) - 40		
ENERAL TECHNICAL INFORMATION						
ightening torque of screws						
	tighteni	ng torque (Nm)			tighte	ning torque (lb-i
		0,60				
ated short-time withstand current lcw		Time (s)				Current (
		1 1				1;
ize of conductor						
omposition of conductor	Min. / Max. value	No	o. of conductor per terminal	Cross section (mm²) or (AWG/kcmil)	Material of the	wire
olid wire	Min.		1	0.5mm ²	Copper	
olid wire	Min.		2	0.5mm²	Copper	
exible wire	Min.		1	0.75mm²	Copper	
exible wire	Min.		2	0.75mm²	Copper	
exible wire	Max.		1	AWG 12	Copper	
exible wire	Max.		1	2.5mm²	Copper	
ingle-core or stranded wire	Max.		1	AWG 12	Copper	
ingle-core or stranded wire exible wire with ferrule according to DIN 46228	Max. Max.		1	2.5mm ² 2.5mm ²	Copper	
exible wire with ferrule according to DIN 46228	Min.		1	0.5mm ²	Copper Copper	
exible wire with ferrule according to DIN 46228	Min.		2	0.5mm²	Copper	
pprobations pecification AC						Marking
no						EAC
E marking						CE
K Directives						
C 60947-3; EN 60947-3; VDE 0660 Teil107						IEC 60947- EN 60947-
L 60947-4-1; CSA C22.2 No. 60947-4-1						CUL US
SA C.22.2 No.14						(1) ®
B/T14048.3						GB/T14048.3
ower loss per pole		_				Power (\
						0,
onditions during transport and storing	(90)		Maximum temperature	· (°C) additional requirements		
Minimum temp						

- Do not lubricate or treat contacts.
- Switches may only be mounted, connected and set into operation by qualified persons according to the accepted rules of technology.





General Information

Text

- Use copper wire only. Do not coat the wire end with tin.
- Terminals with factory fitted jumper links are tightened during production. Take care during installation to ensure factory fitted links are not lost by undoing both sides of linked terminals. After wiring, all terminal screws must be tightened to recommended torque specifications.
- After installation of the switches the spacings between the terminals must be sufficient to fulfill the requirement of the applicable standards.

 Operating temperature
 Min. Temperature [°C]
 Max. Temperature [°C]

55